AD-A108 352 PENNSYLVANIA STATE UNIV UNIVERSITY PARK APPLIED RESE--ETC F/G 9/3
STRUCTURE OF A MULTIBEAM ADAPTIVE SPACE-TIME PROCESSOR.(U)
JUL 81 L H SIBUL, G R SOHIE N00024-79-C-6043
UNCLASSIFIED ARL/PSU/TM-81-156 NL



END
DATE FILMED
-82
DTIC


1.0
1.1
1.25
1.4
1.6
1.8
2.0
2.2
2.5
2.8
3.2
3.6
4.0
MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS 1963-A

(12) LEVEL II

AD A108352

STRUCTURE OF A MULTIBEAM ADAPTIVE SPACE-TIME PROCESSOR

L. H. Sibul and Guy R. L. Sohie

Technical Memorandum
File No. TM 81-156
July 30, 1981
Contract No. N00024-79-C-6043

Copy No. 28

DTIC
ELECTE
DEC 9 1981
B

The Pennsylvania State University
Intercollege Research Programs and Facilities
APPLIED RESEARCH LABORATORY
Post Office Box 30
State College, PA 16801

APPROVED FOR PUBLIC RELEASE

DISTRIBUTION UNLIMITED

NAVY DEPARTMENT

NAVAL SEA SYSTEMS COMMAND

DTIC FILE COPY

81 12 09 053

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE *(When Data Entered)*

REPORT DOCUMENTATION PAGE	READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER: ARL/ TM 81-156	2. GOVT ACCESSION NO.: AD-A108352
3. RECIPIENT'S CATALOG NUMBER	
4. TITLE *(and Subtitle)*: STRUCTURE OF A MULTIBEAM ADAPTIVE SPACE-TIME PROCESSOR	5. TYPE OF REPORT & PERIOD COVERED: Interim
6. PERFORMING ORG. REPORT NUMBER	
7. AUTHOR(s): L. H. Sibul Guy R. L. Sohie	8. CONTRACT OR GRANT NUMBER(s): N00024-79-C-6043
9. PERFORMING ORGANIZATION NAME AND ADDRESS: APPLIED RESEARCH LABORATORY P. O. BOX 30 STATE COLLEGE, PA 16801	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS
11. CONTROLLING OFFICE NAME AND ADDRESS: NAVAL SEA SYSTEMS COMMAND, (SEA 63R1) DEPARTMENT OF THE NAVY WASHINGTON, DC 20362	12. REPORT DATE: July 30, 1981 13. NUMBER OF PAGES: 16
14. MONITORING AGENCY NAME & ADDRESS *(if different from Controlling Office)*	15. SECURITY CLASS. *(of this report)*: UNCLASSIFIED 15a. DECLASSIFICATION/DOWNGRADING SCHEDULE

16. DISTRIBUTION STATEMENT *(of this Report)*

Approved for Public Release. Distribution Unlimited.

Per NAVSEA - September 15, 1981

17. DISTRIBUTION STATEMENT *(of the abstract entered in Block 20, if different from Report)*

18. SUPPLEMENTARY NOTES

19. KEY WORDS *(Continue on reverse side if necessary and identify by block number)*

multibeam, adaptive, processor, beamformer, filter

20. ABSTRACT *(Continue on reverse side if necessary and identify by block number)*

It is shown that an adaptive multi-input, multi-output space-time processor (beamformer and filter) consists of a multi-input, multi-output adaptive processor and a nonadaptive beamsteering operator. The adaptive processor is determined by the spatial and temporal properties of the noise field; whereas, the beamsteering operator is determined a priori by the desired beamsteering directions. In this structure, the multichannel adaptive processor is common to all the desired beamsteering directions.

DD FORM 1 JAN 73 1473 EDITION OF 1 NOV 65 IS OBSOLETE

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE *(When Data Entered)*

Subject: Structure of a Multibeam Adaptive Space-Time Processor

References: See Pages 14 through 16.

ABSTRACT

It is shown that an adaptive multi-input, multi-output space-time processor (beamformer and filter) consists of a multi-input, multi-output adaptive processor and a nonadaptive beamsteering operator. The adaptive processor is determined by the spatial and temporal properties of the noise field; whereas, the beamsteering operator is determined a priori by the desired beamsteering directions. In this structure, the multichannel adaptive processor is common to all the desired beamsteering directions.

TABLE OF CONTENTS

	Page No.
ABSTRACT	1
I. INTRODUCTION	3
II. MULTICHANNEL LIKELIHOOD RATIO PROCESSOR	5
III. ADAPTIVE IMPLEMENTATION OF THE LIKELIHOOD RATIO PROCESSOR	8
IV. CONCLUSION	12
ACKNOWLEDGMENT	13
REFERENCES	14-16

LIST OF FIGURES

Figure No.		Page No.
1	Single Beam Adaptive Array Processor	4
2	Multibeam Adaptive Space-Time Processor	4
3	Implementation of the Inverse Kernel $\underline{Q}(t,u)$	11



I. INTRODUCTION

A number of papers on the adaptive beamforming literature have considered a multi-input, single output adaptive beamformer as shown in Figure 1 [1]-[6]. The comment is usually made that this postulated structure can be used to study adaptive beamformers that have off-broadside beamsteering directions by placing a beamsteerer between the sensors and adaptive beamformer. The difficulty with this approach is that for each new beamsteering direction, the adaptive filter coefficients must be recomputed. If multiple simultaneous beamsteering directions are desired, simultaneous adaptation for all the beamsteering directions becomes intractable.

An alternative approach to the previously cited work is not to postulate a structure in advance, but to let the space-time processor structure evolve from the mathematics for the optimum processor. This approach has been taken by Stocklin [7], Bryn [8], Middleton and Groginsky [9], Adams and Nolte [10], Cox [11], and Bangs and Schultheiss [12] to name a few. The purpose of this note is to point out that the theory of multichannel maximum likelihood processor yields a processor structure that appears to be attractive for adaptive implementation. We shall show that the structure shown in Figure 2 follows naturally from the theory of multichannel maximum likelihood processors. This structure has the advantage that the adaptive part of the processor is determined by the spatial and temporal properties of the noise field and it is common to all beamsteering directions. The adaptive processor is followed by a beamsteering operator which can simultaneously form a



Figure 1. Single beam adaptive array processor



Figure 2. Multibeam adaptive space-time processor

set of beams in all the desired beamsteering directions. The beamsteering operator consists of a set of time delays.

In this paper, lower case letters denote scalars, underlined lower case letters denote vectors, and underlined capital letters denote matrices. The superscripts T, H, and * denote transpose, Hermitian transpose, and complex conjugate. All integrations are carried out over the signal duration T of the active reception interval. $\underline{I}$ denotes identity matrix and $\delta(t-z)$ denotes a delta function. Other symbols are defined in the text.

II. MULTICHANNEL LIKELIHOOD RATIO PROCESSOR

The structure of a multibeam processor for active detection of slowly fluctuating point target in anisotropic, nonstationary, colored Gaussian noise is a generalization of multi-input, single output likelihood ratio processor. The likelihood function for an input vector $\underline{r(t)}$ is

$$\ell_1 = \int_T \underline{v_1^H(u)} \int_T \underline{Q(u,t)}\ \underline{r(t)}\ dt\, du \tag{1}$$

where $v_1(u)$ is the desired signal vector arriving from the direction θ_1, $\underline{Q}(t,u)$ is the matrix inverse kernel that satisfies the integral equation

$$\int_T \underline{R_n(t,u)}\ \underline{Q(u,z)}\ du = \underline{I}\ \delta(t-z), \tag{2}$$

$\underline{R_n(t,u)}$ is the noise covariance matrix [13][14]. The vector of maximum likelihood functions $\underline{\ell}$ is given by

$$\underline{\ell} = \int_T \underline{V^H(u)} \left(\int_T \underline{Q(t,u)}\ \underline{r(t)}\ dt \right) du \tag{3}$$

where $\underline{\ell}^T = [\ell_1, \ell_2 \ldots \ell_L]$ and the matrix $\underline{V(u)}$ is given by:

$$\underline{V(u)} = [\underline{v_1(u)}, \underline{v_2(u)} \ldots \underline{v_L(u)}].$$

The inner integral in Equation 3 is an optimum spatial and temporal smoothing filter where the kernel $\underline{Q(t,u)}$ is determined through Equation 1 from the noise covariance matrix $\underline{R_n(t,u)}$. The covariance matrix $\underline{R_n(t,u)}$ describes the spatial and temporal properties of the anisotropic, colored, and nonstationary noise field. The very essence of the adaptive processing is to "learn" the covariance matrix $\underline{R_n(t,u)}$ from the real data and to find a suitable approximation to the inverse kernel $\underline{Q(u,t)}$. These two steps are the most difficult and computationally most demanding operations in the adaptive processing. Hence, these steps should be done once for all the beamsteering directions. The multiple beamsteering and matched filtering operation is performed by the operator

$$\int_T \underline{V^H(u)} \cdot du$$

A typical term of the vector of likelihood function is

$$\ell_\ell = \int_T \underline{v_\ell^H(u)} \cdot \underline{y(u)}\, du$$

$$= \int_T [v_{\ell 1}^*(u)\, y_1(u) + v_{\ell 2}^*(u)\, y_2(u) \ldots$$

$$\ldots + v_{\ell K}^*\, y_K]\, du \tag{4}$$

where $\underline{y(u)}$ is the output vector of the adaptive matrix filter. Equation 4 indicates that a typical likelihood function is computed by a vector correlation receiver. The meaning of the processor structure becomes clearer if we convert the vector correlation receiver to the vector matched filter form:

$$\ell_\ell = \int_T \underline{h_\ell^H(T-u)}\ \underline{y(u)}\, du \tag{5}$$

where

$$\underline{h_\ell^H(u)} = \underline{v_\ell^H(T-u)} \tag{6}$$

If we now make the usual assumption that the received signals impinging on the sensors or subarrays are identical, except for the relative propagation delays from sensor to sensor*, the ℓ-th received signal vector becomes:

$$v_\ell^T(u) = [s_\ell(u-\tau_1) \ldots s_\ell(u-\tau_k) \ldots s_\ell(u-\tau_K)] \tag{7}$$

*This is not an overly restrictuve assumption because one can easily compensate for different sensor characteristics in the beamformer. Many problems of practical interest fall into this category.

or the vector matched filter can be implemented by a set of delays that will bring the ℓ-th look-direction signal into time coincidence at the ℓ-th output of the beamsteering operator. That is, the beamsteering operator forms a set of uniformly shaded beams in each of the desired look-directions. As it is shown in Figure 2, the outputs of the beamsteering operator are processed by a set of scalar matched filters.

III. ADAPTIVE IMPLEMENTATION OF THE LIKELIHOOD RATIO PROCESSOR

From the previous discussion, it is obvious that the matrix inverse kernel $\underline{Q}(t,u)$ is the only part of the likelihood ratio (LR) processor that is based on information which is not available a priori: the matched filters are uniquely determined by the (known) signals, and the beamsteering is only dependent on the desired look-directions. The matrix inverse kernel $\underline{Q}(t,u)$, on the other hand, is exclusively dependent on the physical properties of the interference and these cannot, in general, be assumed to be known in advance. This clearly suggests an adaptive implementation of this part of the processor.

In order to derive an adaptive realization of the operator $\underline{Q}[\cdot]$ as defined by:

$$(\underline{Q}\ \underline{r})(t) \triangleq \int_T \underline{Q}(t,u)\,\underline{r}(u)\,du \tag{8}$$

where $\underline{Q}(t,u)$ is the solution to the integral Equation 2, it is more convenient to consider the "dual" problem, i.e., the operator:

$$(\underline{H}\,\underline{r})\,(t) = [(\underline{I} - \underline{Q})\underline{r}](t) \triangleq \int_T [\underline{I}\,\delta(t-u) - \underline{Q}(t,u)]\underline{r}(u)\,du$$

$$\triangleq \int_T \underline{H}(t,u)\,\underline{r}(u)\,du \tag{9}$$

where $\underline{H}(t,u)$ satisfies the integral equation (substituting 9 into 2)

$$\int_T \underline{H}(t,u)\underline{R}_n(u,z)\,du = \underline{R}_c(t,z) \tag{10}$$

where $\underline{R}_c(t,z)$ is the correlation function of a "colored" noise component.*

It can be shown from Equation 10 that the linear system $\underline{H}[\cdot]$ corresponds to a minimum mean-square error estimate of this "colored" component based on observation of the input signal $\underline{r}(t)$ over the observation interval (in other words, so-called optimal "smoothing"), since the "orthogonality" condition (Papoulis [15]):

$$E\{[\underline{c}(t) - (\underline{H}\,\underline{r})\,(t)] \cdot \underline{r}^H(u)\} = 0 \qquad t,u \in T \tag{11}$$

reduces to condition (10).

Various interpretations can now be made. While the operator $H[\cdot]$ can be implemented as a MMSE estimator ("smoother") using a multi-

---

*It can be shown (Van Trees [13]) that the relation between this "generalized" colored component and the usual definition of the colored noise $c'(t)$ (where $\underline{R}_c'(t,u)$ does not contain any singularities) is given by:

$$\underline{R}_c(t,u) = \underline{R}_c'(t,u) + (\underline{N} - \underline{I})\,\delta(t-u)$$

where $\underline{N}$ is the matrix of (cross) spectral heights of the temporally uncorrelated noise components.

dimensional version of Widrow's unconstrained LMS algorithm (Widrow [16]), the actual "inverse" filter $\underline{Q}[\cdot]$ which is given by:

$$[\underline{Q}\,\underline{r}](t) = \underline{r}(t) - [\underline{H}\,\underline{r}](t) \triangleq \underline{r}(t) - \hat{\underline{c}}(t) \tag{12}$$

(see Figure 3) is obviously a "noise" canceller (Widrow, et al. [4]).

It is to be noted that under general interference conditions, the LMS algorithm may have unacceptable convergence properties due to the eigenvalue spread of the input correlation matrix (Widrow, et al. [17]). Other structures that have been proposed more recently for noise cancelling applications (Griffiths [18][19]) are the so-called "lattice" or "ladder" configurations, which seem to have efficient convergence behavior as well as interesting roundoff-noise characteristics (Crochiere [20]). While these structures have been primarily used for linear prediction, the smoothing case is only a straightforward extension (Friedlander [21]; Lee, et al. [22]).

As an additional comment, we can add that in the adaptive realization of $\underline{Q}[\cdot]$, only those data should be used which are known to be interference data only. Since, of course, it is unknown a priori whether or not a target is present, those data corresponding to the range in question should be excluded from the data used in the implementation. This obviously limits the application to the case of active sonar or radar.

Finally, we should mention that exactly the same structure as in Figure 2 can be used for maximum likelihood parameter estimation (Van Trees [13]). Thus, parameter estimation does not require different algorithms nor a higher computational load.



Figure 3. Implementation of the inverse kernel $\underline{Q(t,u)}$

IV. CONCLUSION

A structure for the implementation of a likelihood-ratio detector is derived. This structure consists of a "noise canceller" which can be implemented by unconstrained adaptive algorithms, followed by a fixed beamformer and a set of (scalar) matched filters. This structure seems to be more interesting than previous applications where adaptive constrained algorithms were used as adaptive beamformers. Since no constrained algorithms have to be used and the space-time adaptive processor is common to all "look directions", it is suggested that this implementation will be more computationally efficient. Furthermore, since noise cancelling has been extensively studied, various forms for the implementation of the adaptive part of this likelihood-ratio processor are available.

ACKNOWLEDGMENT

This work has been done at the Applied Research Laboratory and has been supported by NAVSEA.

REFERENCES

[1] B. Widrow et al., "Adaptive antenna systems," IEEE Proc., vol. 55, pp. 2143-2159, December 1967.

[2] L. J. Griffiths, "A simple adaptive algorithm for real-time processing in antenna arrays," IEEE Proc., vol. 57, pp. 1696-1704, October 1969.

[3] O. L. Frost, "An algorithm for linearly constrained adaptive array processing," IEEE Proc., vol. 60, pp. 926-935, August 1972.

[4] B. Widrow et al., "Adaptive noise cancelling: principles and applications," IEEE Proc., vol. 63, pp. 1692-1716, December 1975.

[5] N. L. Owsley, "A recent trend in adaptive spatial processing for sensor arrays: constrained adaptation," in Signal Processing, J. W. R. Griffiths, P. L. Stocklin, and C. van Schooneveld, eds., Academic Press, 1973, pp. 591-604.

[6] S. P. Applebaum and D. J. Chapman, "Adaptive arrays with main beam constraints," IEEE Trans. Antennas and Propag., vol. AP-24, pp. 650-662, September 1976.

[7] P. L. Stocklin, "Space-time sampling and likelihood ratio processing in acoustic pressure fields," J. Brit. IRE., vol. 26, pp. 79-90, July 1963.

[8] F. Bryn, "Optimum signal processing of three-dimensional arrays operating on Gaussian signals and noise," J. Acoust. Soc. Am., vol. 34, pp. 289-297, March 1962.

[9] D. Middleton and H. L. Groginsky, "Detection of random acoustic signals and receivers with distributed elements: optimum receiver structures for normal signal and noise fields," J. Acoust. Soc. Am., vol. 38, pp. 727-737, November 1965.

[10] S. L. Adams and L. W. Nolte, "Bayes optimum array detection of targets of known location," J. Acoust. Soc. Am., vol. 58, pp. 656-669, September 1975.

[11] H. Cox, "Interrelated problems in estimation and detection," in Signal Processing, Proceedings of NATO Advanced Study Inst., Enschede, Netherlands, August 1968, pp. 23-1 - 23-67.

[12] W. J. Bangs and P. M. Schultheiss, "Space-time processing for optimal parameter estimation," in Signal Processing, J. W. R. Griffiths, P. L. Stocklin, and C. van Schooneveld, eds., Academic Press, 1973, pp. 577-590.

[13] H. L. Van Trees, Detection, Estimation, and Modulation Theory, Part I, New York : Wiley, 1968, pp. 366-369.

[14] L. H. Sibul and L. J. Ziomek, "Generalized wideband cross-ambiguity function," Proc. 81 IEEE International Conference on Acoustics, Speech and Signal Processing, Atlanta, GA, April 1981, pp. 1239-1242.

[15] A. Papoulis, "Probability, random variables and stochastic processes," McGraw-Hill, New York, 1965.

[16] B. Widrow, "Adaptive filters," in Aspects of Network and System Theory, R. Kalman and N. DeClaris, eds., Holt, Rinehart and Winston, 1971, pp. 563-587.

[17] B. Widrow et al., "Stationary and non-stationary learning characteristics of the LMS adaptive filter," Proc. IEEE, vol. 64, August 1976, pp. 1151-1162.

[18] L. J. Griffiths, "Adaptive structures for multiple-input noise cancelling applications," Proc. 79 IEEE International Conference on Acoustics, Speech and Signal Processing, Washington, DC, April 1979, pp. 925-928.

[19] L. J. Griffiths, "An adaptive lattice structure for noise-cancelling applications," Proc. 78 IEEE International Conference on Acoustics, Speech and Signal Processing, Hartford, CN, April 1978, pp. 87-90.

[20] R. Crochiere, "Digital ladder filter structures and coefficient sensitivity," Res. Lab Electronics Report 103, Man. Inst. Tech., Cambridge, October 1971.

[21] B. Friedlander et al., "Extended Levinson and Chandrasckhar equations for general discrete-time linear estimation problems," IEEE Trans. Autom. Control, vol. AC-23, August 1978, pp. 653-659.

[22] Lee et al., "Recursive least squares ladder estimation algorithms," IEEE Trans. Acoustics, Speech and Signal Processing, vol. ASSP-29, June 1981, pp. 627-641.

DISTRIBUTION LIST -- TM 81-156

NAVSEA, Dr. E. G. Liszka, SEA 63R-1, Copy No. 1
NAVSEA, Mr. D. C. Houser, SEA 63R14, Copy No. 2
NAVSEA, CAPT. R. M. Wellborn, PMS 406, Copy No. 3
NAVSEA, Library, SEA 9961, Copies No. 4 and 5
NUSC, New London, Technical Library, Copy No. 6
NUSC, Newport, Dr. J. R. Short, Code 363, Copy No. 7
NAVELEX, CAPT. Henry Cox, PME 124, Copy No. 8
ONR, Mr. J. G. Smith, Copy No. 9
ARL/UT, Dr. J. F. Willman, Copy No. 10
Marine Physical Laboratory, Dr. K. M. Watson, Copy No. 11
Marine Physical Laboratory, Dr. W. S. Hodgkiss, Copy No. 12
APL/UW, Mr. C. Sienkiewicz, Copy No. 13
DARPA, Dr. Theo. Kooij, Copy No. 14
NCSC, Dr. David Skinner, Code 751, Copy No. 15
University of Rochester, Dr. E. L. Titlebaum, Copy No. 16
ORINCON, 3366 N. Torrey Pines Ct., La Jolla, CA 92037, Dr. Richard A.Altes,Copy No.17
Defense Technical Information Center, Copies No. 18 through 29

FILMED
8